

*****READ & SAVE THESE INSTRUCTIONS *****
ACCESS LIGHTING
MODEL 23062
INSTALLATION & OPERATION INSTRUCTIONS

(1) TOOLS AND MATERIALS REQUIRED

- ❖ BLADE SCREW DRIVER
- ❖ WIRE CUTTERS
- ❖ WIRING SUPPLIES AS REQUIRED BY ELECTRICAL CODE

Attention:

Before assembling your lighting fixture, please read the following instructions. If you feel you do not have sufficient electrical experience, refer to a do-it-yourself wiring handbook or have your fixture installed by a qualified licensed electrician.

(2) GENERAL

1. To ensure the success of the installation, be sure to read these instructions and review the diagrams thoroughly before beginning.
2. All electrical connections must be in accordance with local codes, ordinances, or the National Electrical Code. If you are unfamiliar with methods of installing electrical wiring, secure the services of a qualified licensed electrician.
3. These fixtures are intended for mounting to a standard 4" x 2 1/4" deep metal octagon outlet box. The box must be directly supported by the building structure and U.L. Recognized.
4. Before commencing with the installation, **disconnect the power by turning off the circuit breaker** or by removing the fuse at the fuse box. Turning the power off using the light switch is not sufficient to prevent electrical shock.

NOTE:

The important safeguards and instructions appearing in this manual are not meant to cover all possible conditions and situations that may occur. It must be understood that common sense, caution and care, are factors that cannot be built into any product. These factors must be supplied by the person(s) caring for and operating the fixture.

(3) UNPACKING THE FIXTURE

On checking the contents of the box you will find;

- ❖ Universal Mounting Plate
- ❖ Mounting Hardware
- ❖ Silicone O-Ring
- ❖ Fixture Back Plate with Driver
- ❖ 1 x Metal Shade with 5 W LED Bulb

(4) PREPARE THE FIXTURE

Refer to attached illustration of fixture parts and assembly.

1. If you are replacing an existing fixture disconnect and remove the old fixture. Expose the supply wiring from the outlet box.
2. Using the supplied Allen Key, unscrew the Allen Screws located at the top and bottom of the Metal Shade. Unplug the LED Driver Plug and separate the Fixture Back Plate from the Metal Shade.
3. Secure the Universal Mounting Plate to the Junction Box.
4. Pull the Supply wires through the Center Hole in the Universal Mounting Plate, and through the Center of the Silicone O-Ring.
5. Fit the Silicone-O Ring into the lip located on the back of the Fixture Back Plate.
6. Connect the BLACK supply wire to one LED Driver wire and secure with the supplied Wire Nuts.
7. Connect the WHITE supply wire to the LED Driver Wire and secure with supplied Wire Nuts.
8. Attach the ground (GREEN) wire from the fixture to the outlet box ground terminal (or to the box ground wire).
9. Secure all wire nuts connections with UL listed electrical tape. Tuck wires carefully into Junction box.
10. Position the Fixture Back Plate over the Universal Mounting Plate. Insert the supplied Screws through the Fixture Back Plate and into the holes in the Universal Mounting Plate. Secure by tightening the Screws.
11. Re-attach the Plug for the LED Driver
12. Fit the Metal Shade over the Fixture Back Plate. Align the holes in the top and bottom of the Metal Shade and Fixture Back Plate and secure with the supplied Allen Screws and Allen Key.
13. Restore electricity and check the operation of your new lighting fixture.

CAUTION:

- **Ensure that the Fitting is Cool and Switched off, Before touching.**
- **Do not place the Fixture on or near Combustible Material**

a c c e s s

L I G H T I N G

070208IPV1